

EN - Addendum instruction

Nice S.p.A.
Via Callalta, 1
31046 Oderzo TV Italy
info@niceforyou.com



www.niceforyou.com



The new MCA2R10 control unit (fig.1) replaces the MCA2 control unit (fig.2) and is compatible with the following motors: WG2024, WG3524, WG4024, WG5024, TOO3024, TOO4524 and XME2024 (including for very old models).






• **Changes made to the MCA2R10 control unit terminals:**

- **M1 output:** has been moved to the side of the M2 output
- **RADIO:** a radio receiver with capacity for 100 transmitters has been integrated and the programming key has been added
- **Transformer:** the transformer connection has been modified because the diode bridge is no longer present
- **MOTOR SELECTION:** 4 dip switches have been added for motor type selection
- **OVIEW:** a connector for the IBT4N adapter has been added (connector for the Oview control unit programmer)
- **P.P. Terminal:** renamed "Sbs" = the function has not changed
- **S.C.A.:** renamed "OGI" = the function has not changed
- **OK Led:** under normal conditions, the LED light is green



⚠ All programming procedures are different from the old control unit; it is therefore advisable to read the instruction manual before programming or to check the website www.niceforyou.com or read the QR Code on the control unit silver label.

• Replacing the MCA2 control unit with the new MCA2R10 control unit:

<p>3 A - Remove the 4 screws from the transformer support</p> 	<p>B - Remove the 2 wires that connect the bridge to the transformer</p> 	<p>C - Remove the wires and the diode bridge</p> 	<p>D - Close the transformer support box with the 4 screws</p> 	<p>E - Fix the control unit and connect the transformer cable (a) and the grounding cable (b)</p> 
---	---	---	--	--

EN - Addendum instruction

Nice S.p.A.
Via Callalta, 1
31046 Oderzo TV Italy
info@niceforyou.com


www.niceforyou.com



The new MCA2R10 control unit (fig.1) replaces the MCA2 control unit (fig.2) and is compatible with the following motors: WG2024, WG3524, WG4024, WG5024, TOO3024, TOO4524 and XME2024 (including for very old models).






• **Changes made to the MCA2R10 control unit terminals:**

- **M1 output:** has been moved to the side of the M2 output
- **RADIO:** a radio receiver with capacity for 100 transmitters has been integrated and the programming key has been added
- **Transformer:** the transformer connection has been modified because the diode bridge is no longer present
- **MOTOR SELECTION:** 4 dip switches have been added for motor type selection
- **OVIEW:** a connector for the IBT4N adapter has been added (connector for the Oview control unit programmer)
- **P.P. Terminal:** renamed "Sbs" = the function has not changed
- **S.C.A.:** renamed "OGI" = the function has not changed
- **OK Led:** under normal conditions, the LED light is green



⚠ All programming procedures are different from the old control unit; it is therefore advisable to read the instruction manual before programming or to check the website www.niceforyou.com or read the QR Code on the control unit silver label.

• Replacing the MCA2 control unit with the new MCA2R10 control unit:

<p>3 A - Remove the 4 screws from the transformer support</p> 	<p>B - Remove the 2 wires that connect the bridge to the transformer</p> 	<p>C - Remove the wires and the diode bridge</p> 	<p>D - Close the transformer support box with the 4 screws</p> 	<p>E - Fix the control unit and connect the transformer cable (a) and the grounding cable (b)</p> 
--	--	--	---	---

ISC0673A00MM_03-09-2018

ISC0673A00MM_03-09-2018